

**MBGE ADPT HIMA B, Z VERSION**

**Weidmüller Interface GmbH & Co. KG**  
 Klingenbergstraße 26  
 D-32758 Detmold  
 Germany

www.weidmueller.com



**MiBridge 솔루션.**

마이그레이션용 어댑터 - HIMA HiQuad.

사전 조립된 케이블이 장착된 전면 어댑터는 HIMA HiQuad 카드를 다른 PLC/DCS 시스템이나 바이트몰러의 U-리모트 모듈로 안전하게 전환할 수 있도록 합니다.

**일반 주문 데이터**

주문 번호	8000147254
유형	<a href="#">MBGE ADPT HIMA B, Z VERSION</a>
GTIN (EAN)	4099987172974
수량	ST

## MBGE ADPT HIMA B, Z VERSION

**Weidmüller Interface GmbH & Co. KG**  
 Klingenbergstraße 26  
 D-32758 Detmold  
 Germany

www.weidmueller.com

## 기술 데이터

### 치수 및 중량

깊이	71.4 mm	깊이 (인치)	2.811 inch
높이	127 mm	높이 (인치)	5 inch
너비	19.9 mm	폭 (인치)	0.7835 inch
순중량	99.99 g		

### 온도

보관 온도	-20...70 °C	작동 온도	-20...50 °C
-------	-------------	-------	-------------

### 정격 데이터 UL

보관 온도 UL, 최대	70 °C	작동 온도 UL, 최소	-20 °C
작동 온도 UL, 최대	50 °C	보관 온도 UL, 최소	-20 °C
정격 전류 I 최대	20 A	정격 전압 UN	125 V

### 결선 데이터

폴 수(제어 측)	32극	결선(필드 측)	1756 Control Logix connector
-----------	-----	----------	------------------------------

### 결선 데이터

결선(필드 측)	1756 Control Logix connector	PLC에 결선	신규 PLC 단자대 또는 하드와이어드
폴 수(필드 측)	32 P		

### 정격 데이터

작동 전압	125 V	채널당 최대 전류	2 A
총 작동 전류	20 A		

### 분류

ETIM 8.0	EC002584	ETIM 9.0	EC002584
ETIM 10.0	EC002584	ECLASS 14.0	27-33-02-92
ECLASS 15.0	27-33-02-92		

### 절연 조정(EN50178)

정격 절연 전압	150 V	서지 전압 범주	II
오염 심각도 수준	2	펄스 전압 테스트(1,2/50µs)	1.5 kV
절연 테스트 전압 AC	0.82 kV		

**MBGE ADPT HIMA B, Z VERSION**

**Weidmüller Interface GmbH & Co. KG**  
Klingenbergstraße 26  
D-32758 Detmold  
Germany

도면

[www.weidmueller.com](http://www.weidmueller.com)



The image shows a small, vertically oriented technical drawing or table. It appears to be a terminal block connection diagram for the MBGE ADPT HIMA B, Z VERSION. The drawing is rotated 90 degrees counter-clockwise. It shows a series of terminals with corresponding wire connections and labels. The labels include '1', '2', '3', '4', '5', '6', '7', '8', '9', '10', '11', '12', '13', '14', '15', '16', '17', '18', '19', '20', '21', '22', '23', '24', '25', '26', '27', '28', '29', '30', '31', '32', '33', '34', '35', '36', '37', '38', '39', '40', '41', '42', '43', '44', '45', '46', '47', '48', '49', '50', '51', '52', '53', '54', '55', '56', '57', '58', '59', '60', '61', '62', '63', '64', '65', '66', '67', '68', '69', '70', '71', '72', '73', '74', '75', '76', '77', '78', '79', '80', '81', '82', '83', '84', '85', '86', '87', '88', '89', '90', '91', '92', '93', '94', '95', '96', '97', '98', '99', '100'. The drawing is very small and difficult to read in detail.