


## CMA-51-1250-5A-5VA-0,5

**Weidmüller Interface GmbH & Co. KG**  
 Klingenbergstraße 26  
 D-32758 Detmold  
 Germany

[www.weidmueller.com](http://www.weidmueller.com)



### Plug-on current transformers

Plug-on current transformers are used wherever high currents of up to 5000A need to be measured and processed. Our plug-on current transformers supply secondary currents of 1A or 5A. Weidmüller also offers compact low-power current transformers to convert currents of up to 600 A to voltages of up to 333 mV.

### General ordering data

Version	Primary current: 1250 A, Secondary current max.: 5 A, Load: , Tolerance class: , closed current transformer
Order No.	<a href="#">2680220000</a>
Type	CMA-51-1250-5A-5VA-0,5
GTIN (EAN)	4050118696561
Qty.	1 items
Delivery status	This article will no longer be available in the future.
Available until	2025-04-08T00:00:00+02:00
Manufacturer	MBS AG

**Technical data**

**Approvals**

ROHS Conform

**Dimensions and weights**

Net weight 370 g

**Temperatures**

Storage temperature Operating temperature

**Environmental Product Compliance**

RoHS Compliance Status Compliant  
 REACH SVHC No SVHC above 0.1 wt%

**Dimensions of live conductors**

Type of conductor	Insulated conductor only	Round conductor	43.00 mm
Rail	50 x 12 mm, 40 x 30 mm	Installation location	Indoor use

**Electrical attributes**

Secondary current 0...5 A Primary current 1250 A

**Technical properties**

Protection degree	IP20	Thermal rated continuous current I <sub>thermal</sub>	1.2 x I <sub>rated</sub>
Nominal frequency	50 Hz		

**Classifications**

ETIM 8.0	EC002048	ETIM 9.0	EC002048
ETIM 10.0	EC002048	ECLASS 14.0	27-21-09-02
ECLASS 15.0	27-21-09-02		

**CMA-51-1250-5A-5VA-0,5**

**Weidmüller Interface GmbH & Co. KG**  
Klingenbergstraße 26  
D-32758 Detmold  
Germany

**Drawings**

[www.weidmueller.com](http://www.weidmueller.com)

